USER GUIDE FOR AADHAAR PRINTER DRIVER SETTINGS (IDP SMART 30)

Printer Driver Download Link: http://support.idp-corp.com/viewforum.php?f=8&sid=9d0050640a371a1adbce2c58b2c71c56

STEP 1: Go to "Start" Menu → "Devices and Printers".



STEP 2: Find the active instance of "**IDP SMART-30**" → Right Click → Click on "**Printing Preferences**".



inter State: State: Default Status: 0 document(s) in queue Model: IDP SMART-30 Card Pri... Category: Printer **STEP 3:** In the "**Layout**" tab, select the following settings:

- **Orientation:** Landscape
- Page Order: Front to Back
- Then click on **Advanced** button.

Layout Paper/Ribbon/Printing Side/Media
Orientation:
Landscape
Page Order:
Front to Back 👻
Advanced
OK Cancel Apply

STEP 4: In the same "**Advanced Options**" window, please check whether the given settings are made. You can change the values to as shown in the picture below:

-	IDP	SMART-30 Card Printer Printing Preferences	23			
	ayou	yout Paper/Ribbon/Printing Side/Media				
		IDP SMART-30 Card Printer Advanced Options				
	Or					
	L	IDP SMART-30 Card Printer Advanced Document Settings Document Options Reset Default Values Setup				
	Pa					
	4	📮 🛄 Color Correction				
		Main: <u>0</u>				
		Yellow: 0 =				
		Magenta: U				
		Place 0				
		Diack: 0				
		Besin Black(K) Processing				
		Text: 100				
		Dot: 100				
		Threshold: 50				
		Dithering Degree: 100				
		🖶 👘 Extra Controls				
		Edge Size: <u>20</u>				
		Eject Card: Eject				
	_	Erase Density: 50	H			
		Sharpening: <u>Use</u>				
_	_	Flip Front: Normal				
		Cancel				

STEP 5: Go to the "Paper/Ribbon/Printing" tab & verify the below mentioned settings:

- Supply(S): Auto
- Ribbon(R): hYMCKOKO
- Resin(K): Black Objects

IDP SMART-30 Card Printer Printing Preferences					
Layout Paper/Ribbon/Printing Side/Media					
- Supply Tray Supply(S): Tray(T):	Auto CR80 (54.0mm X 86.0mm)				
- Ribbon Ribbon(R): Resin(K): Split(S):	hYMCKOKO Black Objects Normal				
Printing Mode(M): Speed(S): Color(C): Dither(D):	Standard Standard Iblack & White Diffusion Dither	ß			
	OK Cancel	Apply			

STEP 6: Click on Apply \rightarrow OK \rightarrow Done.

- Now your **IDP SMART-30** Printer is ready for printing Double-Sided Aadhaar Cards.
- You can repeat the above steps for every instance of IDP SMART-30 which is created when you connect the Printer USB cable to a different USB Port.
- This guide has been prepared for use of IDP SMART-30 Double-Sided Card Printer with the YMCKO-KO Half Panel Color Ribbons.

* This User Guide is brought to you by:

SpectroBiz Softech Pvt. Ltd.

Regd. Office: At - Ratanpur, P.O. Krupasindhupur, Dist - Ganjam, Berhampur - 761001, ODISHA. E-mail: <u>info@spectrobiz.com</u> Mob: +91 93794 27535 / 70777 04108

